China HuaMing E&E Co., Ltd www.EMCFittings.Com

HM-2X50A-250V 规格书(交流电源滤波器)

技术参数 Specification

额定电压 Rated voltage250VAC工作频率 Operating frequency50/60Hz额定电流 Rated current50A气候类别 Climatic category10/070/21

试验电压 Test voltage (2s/1Min)

线 - 线 Line-to-line: 1000VDC

线 - 克 Line-to-case: 1000VDC

外形尺寸 Dimension

典型插入损耗	Typical insertion lo	SS

频 率	150KHz-10GHz
插入损耗	100dB

-	180±0.5
120±0.5	
	M24
30	100
	120

电性能 Electrical characteristics

特点与应用 Features & Applications

工作频带宽,插入损耗高:Wide operating band, high insert loss

干扰抑制能力强:Strong ability for restrain interference 低压降,低漏电流:Low voltage drop ,low leakage current

用于电磁屏蔽房、屏蔽柜、电子方舱、信息安全保密房、医院CT、核磁共振房、可控硅变流设备、电源净化设备的电源端的滤波 Use for filter in electro-magnetic mask room、mask cabinet、electronic、square

cabin, information security room, CT equipment of hospital, nuclear-magnetic, resonance room,

SCR current converting equipment, power terminal of the equipments for power purification.