# China HuaMing E&E Co., Ltd WWW.EMCFittings.Com

## HM-EMP-60A-CM 规格书(交流电源滤波器)

## ◆ 技术参数 Specification

额定电压 Rated voltage 230VAC 工作频率 Operating frequency 50/60Hz 额定电流 Rated current 60A 气候类别 Climatic category 10/085/21


试验电压 Test voltage (2s/1Min)


线一线 Line-to-line: 1414VDC 线一壳 Line-to-case: 1414VDC

外形尺寸 Dimension

典型插入损耗 Typical insertion loss

频率	10KHz	14K-18GHz
插入损耗	40dB	100dB





### ◆ 电性能 Electrical characteristics

#### 特点与应用 Features & Applications

工作频带宽,插入损耗高: Wide operating band, high insert loss

干扰抑制能力强: Strong ability for restrain interference

低压降,低漏电流: Low voltage drop, low leakage current

用于电磁屏蔽房、屏蔽柜、电子方舱、信息安全保密房、医院 CT、核磁共振房、可控硅变流设备、电源净化 设备的电源端的滤波 Use for filter in electro-magnetic mask room、mask cabinet、electronic、square cabin、 information security room , CT equipment of hospital, nuclear-magnetic, resonance room, SCR current converting equipment, power terminal of the equipment for power purification.